

## Audio Amplifier PA2

**Features:**

- Mini Amplifier(Class D), with MIC mixer
- 2x 20 Watt@4 Ohm default output
- 1x 40 Watt@8 Ohm bridge output
- Dual-mono output
- 2 Stereo audio selectable inputs
- Microphone mixer, with independent volume control
- Auto noise gate for Mic input
- Volume / Bass / Treble adjustable separately
- Local buttons + RS232 + IR controlling
- 24 V DC power supply.
- RS-232: controlling function, with smart feedback.



**Technical Data**

**Dimensions**

(WxHxD)	125 x 40 x 90mm
Weight	265 g (ohne Netzteil)
Power supply	24 V DC

**Connectors**

Input 1	Stereo Line, RCA
Input 2	Stereo Line, 3,5 mm jack
Input 3	Mic Mono, unsymmetrisch, 6,3 mm Klinke
Input impedance	>10 kΩ
Frequency response	20 – 20 kHz, ± 3 dB
THD	1% / 1 kHz
Output power Stereo	2 x 20 W @ 4 Ohm
Output power Dual Mono	2 x 20 W @ 4 Ω
Output power Brücke Mono	1 x 40 W @ 8 Ω
Output 1	Stereo Phoenix srew, 4 Pin
Output impedance	4-8 Ω
Output 2	Stereo Line, 3,5 mm jack
Output impedance	< 50 Ω
RS-232	Phoenix screw, 3 Pin
IR	Phoenix screw, 3 Pin
Delivery	Amplifier, Phoenix connector, multi-voltage power supply, user manual



Type	Item No.
Audio Amplifer PA2	05300100